

# 1206 Keramik Chip Kondensatoren



**Selection Chart: 1206, COG Class 1 (+/- 30ppm/°C)**

**RoHS COMPLIANT**

Capacitance Range

Cap pF	Size	Tol	2000V	1500V	1000V	630V	500V	250V
10	1206	5	1206N100J202NT		1206N100J102NT			
11	1206	5	1206N110J202NT		1206N110J102NT			
12	1206	5	1206N120J202NT		1206N120J102NT			
15	1206	5	1206N150J202NT		1206N150J102NT			
18	1206	5	1206N180J202NT		1206N180J102NT			
20	1206	5	1206N200J202NT	1206N200J152NT	1206N200J102NT			
22	1206	5	1206N220J202NT	1206N220J152NT	1206N220J102NT			
27	1206	5	1206N270J202NT	1206N270J152NT	1206N270J102NT			
33	1206	5	1206N330J202NT	1206N330J152NT	1206N330J102NT			
47	1206	5	1206N470J202NT	1206N470J152NT	1206N470J102NT			
56	1206	5	1206N560J202NT	1206N560J152NT	1206N560J102NT			
68	1206	5	1206N680J202NT	1206N680J152NT	1206N680J102NT			
82	1206	5	1206N820J202NT	1206N820J152NT	1206N820J102NT			
100	1206	5	1206N101J202NT	1206N101J152NT	1206N101J102NT	1206N101J631NT	1206N101J501NT	1206N101J251NT
150	1206	5	1206N151J202NT	1206N151J152NT	1206N151J102NT	1206N151J631NT	1206N151J501NT	1206N151J251NT
220	1206	5	1206N221J202NT	1206N221J152NT	1206N221J102NT	1206N221J631NT	1206N221J501NT	1206N221J251NT
330	1206	5	1206N331J202NT	1206N331J152NT	1206N331J102NT	1206N331J631NT	1206N331J501NT	1206N331J251NT
390	1206	5	1206N391J202NT	1206N391J152NT	1206N391J102NT	1206N391J631NT	1206N391J501NT	1206N391J251NT
470	1206	5		1206N471J152NT	1206N471J102NT	1206N471J631NT	1206N471J501NT	1206N471J251NT
560	1206	5		1206N561J152NT	1206N561J102NT	1206N561J631NT	1206N561J501NT	1206N561J251NT
680	1206	5			1206N681J102NT	1206N681J631NT	1206N681J501NT	1206N681J251NT
820	1206	5			1206N821J102NT	1206N821J631NT	1206N821J501NT	1206N821J251NT
1000	1206	5			1206N102J102NT	1206N102J631NT	1206N102J501NT	1206N102J251NT
1500	1206	5				1206N152J631NT	1206N152J501NT	1206N152J251NT
2200	1206	5						1206N222J251NT 3.9nF max

**Selection Chart: 1206, X7R Class 2 (+/- 15%)**

**RoHS COMPLIANT**

Capacitance Range

Cap pF	Size	Tol	2000V	1500V	1000V	630V	500V	250V
120	1206	10	1206B121K202NT	1206B121K152NT				
220	1206	10	1206B221K202NT	1206B221K152NT				
330	1206	10	1206B331K202NT	1206B331K152NT				
470	1206	10	1206B471K202NT	1206B471K152NT	1206B471K102NT			
1000	1206	10	1206B102K202NT	1206B102K152NT	1206B102K102NT	1206B102K631NT	1206B102K501NT	1206B102K251NT
1500	1206	10		1206B152K152NT	1206B152K102NT	1206B152K631NT	1206B152K501NT	1206B152K251NT
2200	1206	10		1206B222K152NT	1206B222K102NT	1206B222K631NT	1206B222K501NT	1206B222K251NT
2700	1206	10			1206B272K102NT	1206B272K631NT	1206B272K501NT	1206B272K251NT
3300	1206	10			1206B332K102NT	1206B332K631NT	1206B332K501NT	1206B332K251NT
4700	1206	10			1206B472K102NT	1206B472K631NT	1206B472K501NT	1206B472K251NT
6800	1206	10			1206B682K102NT	1206B682K631NT	1206B682K501NT	1206B682K251NT
10nF	1206	10				1206B103K631NT	1206B103K501NT	1206B103K251NT
22nF	1206	10				15nF max	1206B223K501NT	1206B223K251NT
47nF	1206	10						1206B473K251NT
56nF	1206	10						1206B563K251NT

BREDEMEIER ELECTRONICS GMBH TEL. +49 (89) 90 80 24 Fax +49 (89) 9437 9546

info@bredemeiergmbh.de [www.bredemeiergmbh.de](http://www.bredemeiergmbh.de)