

1812 Keramik Chip Kondensatoren



Selection Chart: 1812, COG Class 1 (TCC +/- 30ppm/°C) RoHS COMPLIANT
 Capacitance Range

Cap pF	Size	Tol	3000V	2000V	1000V	630V	500V	250V
10	1812	5	1812N100J302NT					
12	1812	5	1812N120J302NT					
15	1812	5	1812N150J302NT					
18	1812	5	1812N180J302NT					
22	1812	5	1812N220J302NT		1812N220J102NT			
27	1812	5	1812N270J302NT					
33	1812	5	1812N330J302NT		1812N330J102NT			
39	1812	5	1812N390J302NT					
47	1812	5	1812N470J302NT		1812N470J102NT			
56	1812	5	1812N560J302NT					
68	1812	5	1812N680J302NT		1812N680J102NT			
82	1812	5	1812N820J302NT					
100	1812	5	1812N101J302NT	1812N101J202NT	1812N101J102NT			
120	1812	5	1812N121J302NT	1812N121J202NT	1812N121J102NT			
150	1812	5	1812N151J302NT	1812N151J202NT	1812N151J102NT			
220	1812	5	1812N221J302NT	1812N221J202NT	1812N221J102NT			
270	1812	5	1812N271J302NT	1812N271J202NT	1812N271J102NT			
330	1812	5	1812N331J302NT	1812N331J202NT	1812N331J102NT			
470	1812	5	1812N471J302NT	1812N471J202NT	1812N471J102NT			
680	1812	5	1812N681J302NT	1812N681J202NT	1812N681J102NT			
1000	1812	5	1812N102J302NX	1812N102J202NT	1812N102J102NT	1812N102J631NT	1812N102J501NT	1812N102J251NT
1200	1812	5	1812N122J302NX	1812N122J202NT	1812N122J102NT	1812N122J631NT	1812N122J501NT	1812N122J251NT
1500	1812	5		1812N152J202NT	1812N152J102NT	1812N152J631NT	1812N152J501NT	1812N152J251NT
2700	1812	5		1812N272J202NX	1812N272J102NT	1812N272J631NT	1812N272J501NT	1812N272J251NT
3300	1812	5			1812N332J102NT	1812N332J631NT	1812N332J501NT	1812N332J251NT
4700	1812	5			1812N472J102NT	1812N472J631NT	1812N472J501NT	1812N472J251NT
10nF	1812	5			8.2nF max	1812N103J631NT	1812N103J501NT	1812N103J251NT
22nF	1812	5					12nF max	1812N223J251NT

Selection Chart: 1812, X7R Class 2 (TCC +/- 15%) RoHS COMPLIANT
 Capacitance Range

Cap pF	Size	Tol	3000V	2000V	1000V	630V	500V	250V
1000	1812	10	1812B102K302NT	1812B102K202NT	812B102K102NT	1812B102K631NT		
1500	1812	10	1812B152K302NT	1812B152K202NT	812B152K102NT	1812B152K631NT		
2200	1812	10	1812B222K302NX	1812B222K202NT	812B222K102NT	1812B222K631NT		
2700	1812	10	1812B272K302NX	1812B272K202NT	812B272K102NT	1812B272K631NT		
3300	1812	10		1812B332K202NT	812B332K102NT	1812B332K631NT		
4700	1812	10		1812B472K202NT	812B472K102NT	1812B472K631NT		
6800	1812	10		1812B682K202NX	812B682K102NT	1812B682K631NT		
10nF	1812	10		1812B103K202NX	812B103K102NT	1812B103K631NT	1812B103K501NT	1812B103K251NT
22nF	1812	10			812B223K102NT	1812B223K631NT	1812B223K501NT	1812B223K251NT
47nF	1812	10			1812B473K102NX	1812B473K631NT	1812B473K501NT	1812B473K251NT
100nF	1812	10				1812B104K631NT	1812B104K501NT	1812B104K251NT
220nF	1812	10				120nF max	150nF max	1812B224K251NT
470nF	1812	10						1812B474K251NX

BREDEMEIER ELECTRONICS GMBH TEL. +49 (89) 90 80 24 Fax +49 (89) 9437 9546

info@bredemeiergmbh.de www.bredemeiergmbh.de